



44 FARRAND STREET
BLOOMFIELD, NJ 07003
(973) 748-5089

NTE727

Integrated Circuit

Four Independent AC Amplifiers

Description:

The NTE727 is a silicon monolithic integrated circuit in a 16-Lead DIP type package consisting of four independent identical AC amplifiers which can operate from a single-ended power supply.

The amplifiers include internal DC bias and feedback to provide temperature-stabilized operation. They may be used in a wide variety of AC applications in which operational amplifiers have previously been used.

Each high gain amplifier has a high impedance non-inverting input, and a lower impedance inverting input for the application of feedback. Two power-supply terminals and two ground terminals are provided to reduce internal and external coupling between amplifiers.

Features:

- Four AC Amplifiers on a Common Substrate
- Independently Accessible Inputs and Outputs
- Operates from a Single-Ended Supply
- Noise Figure (Each Amp): 2dB Typ @ 1kHz
- High Voltage Gain (Each Amp): 53dB Min
- High Input Resistance (Each Amp): 90k Ω Typ
- Undistorted Output Voltage (Each Amp): 2V_{rms} Min
- Output Impedance (Each Amp): 1k Ω Typ
- Open-Loop Bandwidth (Each Amp): 300kHz Typ

Applications:

- Multi-Channel or Cascade Operation
- Low-Level Preamplifiers
- Equalizers
- Linear Signal Mixers
- Tone Generators
- Multivibrators
- AC Intergrators

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Power Supply Voltage	+16V
AC Input Voltage	0.5V _{rms}
Power Dissipation ($T_A = +55^\circ\text{C}$), P_D	750mW
Derate Above 55°C	7.7mW/ $^\circ\text{C}$
Operating Temperature Range, T_{opr}	-40° to +85°C
Storage Temperature Range, T_{stg}	-65° to +150°C

Electrical Characteristics: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit	
Static ($V_{CC} = 12\text{V}$)							
Current Drain Per Amplifier Pair	I_{12} or I_{15}	9.5	13.5	17.5	mA	
DC Voltage at Output Terminals	$V_1, V_6,$ V_{11}, V_{16}	6.1	6.9	8.1	V	
DC Voltage at Feedback Terminals	$V_3, V_7,$ V_{10}, V_{14}	1.7	2.0	2.3	V	
DC Voltage at Input Terminals	$V_4, V_8,$ V_9, V_{13}	2.2	2.5	2.8	V	
Dynamic (Characteristics given are for each amplifier with no AC feedback)							
Open-Loop Gain	AOL	$V_{CC} = 12\text{V}, E_{IN} = 2\text{mV}, f = 10\text{kHz}$	53	58	—	dB	
Output Voltage Swing	$V_O(\text{rms})$	$V_{CC} = 12\text{V}, f = 1\text{kHz}, \text{THD} = 5\%$	2.0	2.4	—	V	
Open-Loop -3dB Bandwidth	BW	$V_{CC} = 12\text{V}, E_{IN} = 2\text{mV}$	250	300	0	kHz	
Total Harmonic Distortion	THD	$V_{CC} = 12\text{V}, f = 1\text{kHz}, E_{OUT} = 2\text{V}_\text{rms}$	—	0.65	—	%	
Input Resistance	R_{IN}	Open Loop, $f = 1\text{kHz}$, Note 1	—	90	—	kΩ	
Input Capacitance	C_{IN}	$f = 1\text{MHz}$	—	9	—	pF	
Output Resistance	R_{OUT}	Note 1	—	1	—	kΩ	
Output Capacitance	C_{OUT}	$f = 1\text{MHz}$	—	18	—	pF	
Feedback Capacitance (Output to Non-Inverting Input)	C_{FB}	$V_{CC} = 12\text{V}, f = 1\text{MHz}$	—	<0.1	—	pF	
Broad-Band Output Noise Voltage	E_N	$V_{CC} = 12\text{V}, R_S = 10\text{k}\Omega, A = 40\text{dB},$ Equivalent Noise BW = 50kHz	—	0.3	1.0	mV	
Output Noise Voltage "Weighted"	$E_{N(WT)}$	—	0.5	2.2	mV	
Noise Figure	NF	$R_S = 5\text{k}\Omega$	$f = 10\text{Hz}$	—	10.0	—	dB
			$f = 100\text{Hz}$	—	5.8	—	dB
			$f = 1\text{kHz}$	—	2.0	—	dB
			$f = 10\text{kHz}$	—	1.1	—	dB
			$f = 100\text{kHz}$	—	0.6	—	dB
Inter-Amplifier Audio Separation "Crosstalk"	CT	$V_{CC} = 12\text{V}, f = 1\text{kHz}, 0\text{dB} = 0.78\text{V}$	—	<-45	—	dB	
Inter-Amplifier Capacitance (Any amplifier output to any other amplifier input)	C	$V_{CC} = 12\text{V}, f = 1\text{MHz}$	—	<0.02	—	pF	

Note 1. Pin3, Pin7, Pin10, and Pin14 are bypassed to GND.

Pin Connection Diagram

