Heraeus

1 Pt500 KN 3026 E

The KN Series Ceramic Wire Wound PRTDs are suitable for general applications requiring temperature stability.

Applications: Industrial resistance thermometers, especially in chemical, power generation plants and analytical equipment.

Construction: A platinum coil is sealed inside a high purity aluminum oxide ceramic body. Lead wires are shear force resistant and assure proper connection to extension leads and cables.



| Models | | | | | | | | | |
|------------------|------------------------|--------------------------|------------------|----------|-----------|----------|----------------------------|--------------------------------------|-----------------------------------|
| Description | Tolerance IEC 60751 | Order No. | Dimensions mm | | | | Self Heating 0°C (K/mW) | Respons Water current V=0.4m/s | |
| | | | L | D | d | I | | t _{0.5} t _{0.9} | t _{0.5} t _{0.9} |
| 1Pt500 KN 3026 E | W0.3 W0.15 | 32.206.331 32.206.332 | 30-0 | 2.6±0.15 | 0.27±0.01 | 10.0±0.5 | 1 | To be released soon | |

| 1Pt500 KN 3026 E | W0.15 | 32.206.332 | 30-0 | 2.6±0.15 | 0.27±0.01 | 10.0±0.5 | lo be released soon | | |
|---------------------------------------|--|------------|------------|---------------|------------------|-------------------------------|--|--|--|
| Technical Specification | | | | | | | | | |
| Nominal resistance: | 500 Ohi | m @ 0 °C | | | Measurir | g current: | 1 mA | | |
| Temperature range: | W0.3 (Class B) = -196 to +660 °C W0.15 (Class A) = -196 to +600 °C | | | | Tolerance class: | | According to old JIS Other standards and narrower tolerances are available on request | | |
| Temperature coefficient: | Tc = 3916 ppm/K | | | Tempera | ture stability: | Excellent long-term stability | | | |
| Leads: | Palladium-gold alloy | | | | Also avai | lable: | Platinum-gold alloy Different temperature coefficients (3850 ppm/K - IEC 60751:2008) Extension leads Two separated coils can be embedded in one ceramic body | | |
| Insulation resistance after assembly: | > 100 MOhm @ 25 °C | | | | | | | | |
| The measuring point is | located at | 8 mm from | the end of | the sensor bo | dy | | • • | | |

Heraeus Sensor Technology USA

1901 Route 130 North Brunswick, NJ 08902 Phone 732-940-4400 Fax 732-940-4445 Email info.hst-us@heraeus.com www.hst-us.com

Status: HSTUSA 10/09