

SPECIFICATION SHEET
JFW MODEL 50BR-017
BENCH TOP ROTARY ATTENUATOR

JFW Industries, Inc.
 Phone: 317-887-1340
 sales@jfwindustries.com
 www.jfwindustries.com

Frequency Range	DC-1000 MHz
Impedance	50 Ohms nominal
Attenuation Range	0-81 dB in 0.1 dB steps
VSWR	1.3:1 maximum DC-500 MHz 1.5:1 maximum 500-1000 MHz
Attenuation Accuracy	DC-500 MHz ± 0.04 dB (0-1 dB) ± 0.2 dB (1-10 dB) ± 0.5 dB (10-81 dB) 500-1000 MHz ± 0.06 dB (0-1 dB) ± 0.3 dB (1-10 dB) ± 0.8 dB (10-81 dB)
Insertion Loss	1.25 dB
RF Input Power	2 Watts average 1000 Watts peak
RF Connector	N, BNC, SMA or TNC female
Physical Size	See outline drawing 092-1085

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	01/04/1989			17479	07/28/2009	C	TRS 07/28/2009
9999	05/05/2003	A	TRS 02/24/2004				
14523	08/07/2007	B	TRS 08/07/2007				