

DESCRIPTION


The Accutek AK5916384S high density memory module is a CMOS random access memory organized in 16 Meg x 9 bit words. The assembly consists of nine 16 Meg x 1 DRAMs in plastic SOJ packages mounted on the front side of a printed circuit board in 30 pad SIM (leadless) or 30 pin SIP (leaded) configuration. The module is only 0.8 inch high (same height as standard 1 Meg modules), making it ideally suited for applications with low height restrictions.

The operation of the AK5916384 is identical to nine 16 Meg x 1 dynamic RAMs. For the lower eight bits data input is tied to data output and brought out separately for each device, with common RAS, \overline{CAS} and \overline{WE} control. This common I/O feature dictates the use of early-write cycles to prevent contention of D and Q. Since the Write-Enable (\overline{WE}) signal must always go low before \overline{CAS} in a write cycle, Read-Write and Read-Modify-Write operation is not possible. For the ninth bit, the data input (D₉) and the data output (Q₉) pins are brought out separately and controlled by a separate \overline{PCAS} for that bit. Bit nine is generally used for parity.

FEATURES

- 16,777,216 x 9 bit organization
- Optional 30 Pad leadless SIM (Single In-Line Module) or 30 Pin leaded SIP (Single In-Line Package)
- JEDEC standard pinout
- Common CAS and RAS control for the lower eight bits
- Separate PCAS control for D₉ and Q₉
- CAS-before-RAS refresh

AK5916384S / AK5916384G 16,777,216 Word by 9 Bit CMOS Dynamic Random Access Memory



- Downward compatible with AK594096, AK591024, and AK59256
- · TTL-Compatible Inputs and Outputs
- RAS-Only Refresh
- 4096 Cycle Refresh every 64mSEC
- Power: 4.45 Watt Max Active (60 nS) 3.96 Watt Max Active (70 nS) 49.5 mWatt Max Standby
- Operating free air temperature 0°C to 70°C
- · Fast Page Mode
- 8 Bit version (without parity bit) also available

PIN NOMENCLATURE

DQ ₁ - DQ ₈	Data In/Data Out
D ₉	Data In
Q ₉	Data Out
A ₀ - A ₁₁	Address Inputs
CAS, PCAS	Column Address Strobe
RAS	Row Address Strobe
WE	Write Enable
Vcc	5v Supply
Vss	Ground
NC	No Connect


MODULE OPTIONS

Leadless SIM: AK5916384S Leaded SIP: AK5916384G

PIN ASSIGNMENT

PIN#	SYMBOL	PIN#	SYMBOL
1	Vcc	16	DQ5
2	CAS	17	A8
3	DQ1	18	A9
4	A0	19	A10
5	A1	20	DQ6
6	DQ2	21	WE
7	A2	22	Vss
8	А3	23	DQ7
9	Vss	24	A11
10	DQ3	25	DQ8
11	A4	26	Q9
12	A5	27	RAS
13	DQ4	28	PCAS
14	A6	29	D9
15	A7	30	Vcc

FUNCTIONAL DIAGRAM



ORDERING INFORMATION

PART NUMBER CODING INTERPRETATION

Position 1 2 3 4 5 6 7 8

1 Product

AK = Accutek Memory

2 Type

4 = Dynamic RAM

5 = CMOS Dynamic RAM

6 = Static RAM

3 Organization/Word Width

1 = by 1 16 = by 16 4 = by 4 32 = by 32 8 = by 8 36 = by 36

9 = by 9

4 Size/Bits Depth

64 = 64K 4096 = 4 MEG 256 = 256K 8192 = 8 MEG 1024 = 1 MEG 16384 = 16 MEG

5 Package Type

G = Single In-Line Package (SIP)

S = Single In-Line Module (SIM)

D = Dual In-Line Package (DIP)

W = .050 inch Pitch Edge Connect

Z = Zig-Zag In-Line Package (ZIP)

6 Special Designation

P = Page Mode

N = Nibble Mode

K = Static Column Mode

W = Write Per Bit Mode

V = Video Ram

7 Separator

- = Commercial 0° C to + 70° C

M = Military Equivalent Screened

(-55°C to +125°C)

I = Industrial Temperature Tested

 $(-45^{\circ}C \text{ to } +85^{\circ}C)$

X = Burned In

8 Speed (first two significant digits)

DRAMS SRAMS
60 = 60 nS 8 = 8 nS
70 = 70 nS 12 = 12 nS
80 = 80 nS 15 = 15 nS

The numbers and coding on this page do not include all variations available but are shown as examples of the most widely used variations. Contact Accutek if other information is required.

EXAMPLES:

AK5916384SP-70

16 Meg x 9, 70 nSEC, Leadless SIM, Fast Page Mode

AK5916384GP-60

16 Meg x 9, 60 nSEC, Leaded SIP, Fast Page Mode



ACCUTEK MICROCIRCUIT CORPORATION


BUSINESS CENTER at NEWBURYPORT 2 NEW PASTURE ROAD, SUITE 1 NEWBURYPORT, MA 01950-4054

PHONE: 978-465-6200 FAX: 978-462-3396

Email: sales@accutekmicro.com Internet: www.accutekmicro.com

MECHANICAL DIMENSIONS

Inches



Accutek reserves the right to make changes in specifications at any time and without notice. Accutek does not assume any responsibility for the use of any circuitry described; no circuit patent licenses are implied. Preliminary data sheets contain minimum and maximum limits based upon design objectives, which are subject to change upon full characterization over the specific operating conditions.